

5. RF 6 Key Controller(Aluminum Case) (ZJ-RF62)

Description

RF 6 Key Controller is a product of updating computer IC. It is applied in various LED Lighting. It features Easy Wiring and Easy Operation. It can create lighting effects such as Flash, Fade in/out, Blink and so on.

Specification

- Working Temperature: -20-60°C
- Working Voltage: DC12V ,24V Optional(To be indicated when order)
- Output: 3 channels
- Wiring Mode: common anode and cathode
- Size: L95XW89XH26 mm
- Net Weight: 185g
- Max. Load Current: <4A/channel
- Output Watt: 12V: <144W, 24V: <288W



User Manual

1. Connect load first. Then wire input. Make sure there is not short circuit before it is powered on.

2. keys on the remoter are:

ON/OFF: Switch On/Off the controller

MODE: Lighting Effect Programs, total 21 programs built-in

B+: Brightness Up, total 256 grades, 1 grade per press

B-: Brightness Down, total 256 grades, 1 grade per press

S+: Speed Up, 100 grades, 1 grade per press

S-: Speed Down, 100 grades, 1 grade per press

3. Typical Lighting Effect:

No.	Lighting Effect	Remark	No.	Lighting Effect	Remark
1	Static Red	Brightness is adjustable	12	Red Blink	Both Brightness and Speed are adjustable
2	Static Blue		13	Blue Blink	
3	Static Mauve		14	Mauve Blink	
4	Static Green		15	Green Blink	
5	Static Yellow		16	Yellow Blink	
6	Static Dark Green		17	Dark Green Blink	
7	Static White		18	White Blink	
8	R, G and B Flash	Both Brightness and Speed are adjustable	19	Red and Blue Fade in/out	Speed is adjustable
9	7 Color Flash	Speed is adjustable	20	Blue and Green Fade in/out	
10	R, G and B Fade in/out	Speed is adjustable	21	Green and Red Fade in/out	
11	7 Color Fade in/out				

Typical Application

